









Attention: Read and understand these instructions before installing fixture. This fixture is intended for installation in accordance with National Electric Code and local regulation: To assure full compliance with local codes and regulations, check with your local electrical inspector before installation. This equipment is guaranteed only when used as indicated in these instructions; therefore they should be kept for future reference. To prevent electrical shock, turn off power supply before carrying out any connection or maintenance operations.




Make sure you have all the elements to complete the installation. Depending on configuration selected, you must have the following:

Driver Housing	<p>Surface model</p> 	<p>Recessed model</p> 
Grafa Fixture	<p>Rectangle model</p> 	<p>Square model</p> 
Mounting Clip/ Cable Kit	<p>Models may vary</p> 	




STEP 1 (cont.)

Depending on the configuration, establish where the housing(s) will be placed in order to feed the module(s).




Allows connection of a single Grafa/Pad fixture




Allows connection of 2x Grafa/Pad Fixtures as a system


1 Module = 1 Driver Housing with Single driver configuration (S)




2 Modules = 1 Driver Housing with Dual driver configuration (D)




3 Modules = 2 Driver Housings, 1 with Single (S) and 1 with Dual (D) driver configuration.
(S) fed module must not be connected electrically with (D).



3 Modules (alternate configuration) = 2 Driver Housings, 1 with Dual driver configuration (D)
and 1 with Single driver configuration (S)





4 Modules = 2 Driver Housings with Dual driver configuration (D)
(D1) fed module must not be connected electrically with (D2).






STEP 1 (Cont.)

Depending on the suspension brackets you use, the suspension points will have different spacing. Mark the location of the suspension points related to your configuration prior to installation using the information that follows:




Actual fixture dimensions for reference




(continued on next page)




STEP 1 (Cont.)




● clip 1 module




■ clip 2 module




▲ clip 3 module



★ clip 4 module





◆ clip linking Rectangle + Square modules





STEP 2



Install the Driver Housing(s) depending on your configuration, following the Instruction sheet supplied with it (document Y503-11401).



STEP 3

Install the suspension cable couplers to the ceiling to the marked locations using the proper hardware (not supplied)

4x









STEP 4

Install the suspension clips depending on your configuration.



Joining 1 fixture



Joining 2 fixtures



Joining 3 fixtures





(continued on next page)






STEP 4 (Cont.) Install the suspension clips depending on your configuration.

Joining 4 fixtures



Joining a square fixture with a rectangular






STEP 5

Feed the Suspension cables through the couplers and screw the grippers in.



5.2




STEP 6

6.1 Loosen the bottom of the cable gripper in order to adjust fixture height. Pressing on it unlocks cable movement
6.2 Once fixture is level enough, tighten bottom of the cable gripper in order to lock it into position.

6.1





6.2





STEP 6 (cont.)


6.3 Rotate the micro adjustment wheel on the bottom of the suspension cable to get a perfectly leveled fixture.





STEP 7

7.1 On the fixture, lift up the terminal cover to expose the wiring connections.
7.2 Remove the screws holding the strain relief bracket.
7.3 Route the power cable into the fixture and connect it to the location labeled "A". Reinstall the strain relief bracket. If only connecting one fixture, clip the cover back on, installation is complete. If not, continue to Step 8


7.1




7.2



7.3




7.4





STEP 8

7.4 To connect two modules electrically, provided you are using the correct 2-driver housing, use the jumper cable that comes with the driver housing. Connecting the 2-pin end of the jumper to the first fixture's B location, and the other end (4-pin) to the second fixture's A location.





STEP 8 (cont.)

Place the cover back on, ensuring the jumper cable wires and electrical cable are neatly routed. Screw on the wire cover to seal up the fixture. Installation is complete.

