



**Attention:** Read and understand these instructions before installing fixture. This fixture is intended for installation in accordance with National Electric Code and local regulation: To assure full compliance with local codes and regulations, check with your local electrical inspector before installation. This equipment is guaranteed only when used as indicated in these instructions; Therefore they should be kept for future reference. To prevent electrical shock, turn off power supply before carrying out any connection or maintenance operations.





**Attention:** Tagora 970 luminaires should be installed and held by 2 persons at least. It is highly recommended not to hold Tagora 970 by one side, this would deform the shape of the body.

### STEP 1

Install canopy to the ceiling  
The luminaire should not be held by electrical J-box

1. Unscrew part E
2. Remove part G
3. Unscrew part D
4. Fix part B to the ceiling - building structure (screws not included)
5. Make the appropriate electrical connection
6. Push the wires inside the J-box
7. Fix part C to part B (screws included)
8. Screw part D to hold electrical wire,



FIXTURE WIRES	CEILING WIRES	FOR DIMMABLE VERSION	CEILING WIRES
GREEN	GREEN	FIXTURE WIRES	
BLACK	BLACK	PURPLE +	0-10VDC +
WHITE	WHITE	GREY -	DC -





**STEP 2**

**Steel cables adjustment**

1. Loosen part H
2. Adjust all cables to required height
3. Tighten part H
4. Cut extra steel cables.

5. Fix part G to C (initial position)
6. Screw part E to hold Part G





**STEP 3**

Install the body

1. Loosen wing nuts
2. Remove the baffle from the body
3. Install the 8 fluorescent tubes inside the body
4. Install the diffuser on the baffle

5. Reinstall the baffle to the body
6. Push the diffuser 2" to the top
7. Tighten wing nuts

